

SBFTF10xx-10x

Stand-alone Fast Ethernet Media and Rate Converter

10/100Base-TX to 100Base-FX



SBFTF1014-105

Features

- Auto-Negotiation
- Auto-MDI/MDIX
- Link Pass Through
- Far-End-Fault (FEF) Detection
- Automatic Link Restoration Extend network distance up to 120km
- Bridging devices will provide conversion and integration solutions for half and full-duplex environments
- 10 Mbps or 100 Mbps on TP port
- Half or full-duplex on all ports including fiber

The SBFTF10xx-105 provides an interface between 10/100Base-TX ports and 100Base-FX ports, allowing users to integrate fiber optic cabling into 10/100Base-TX copper environments.

Operating at Layer 2, this converter not only converts copper to fiber, but it also does Rate Conversion, converting 10/100 copper to 100Base fiber.

Specifications

Standards	IEEE 802.3
Data Rate	10 Mbps; 100 Mbps, Layer 2
Filtering Addresses	1K MAC addresses
Filtering & Forwarding	14,880 pps for Ethernet; Rate 148,800 pps for Fast Ethernet
RAM Buffers	512 KB
Max Packet Size	2044 bytes untagged; 2048 bytes tagged
Switches	SW1 (TP): Auto-Negotiation On/Off SW2 (TP): Half or Full-duplex with Auto-Negotiation Off SW3 (TP): 10Mbps or 100 Mbps with Auto-Negotiation Off SW4 (Fiber): Half or Full-duplex SW5: Link Pass Through On/Off SW6: Far-End-Fault (FEF) On/Off
Status LEDs	PWR (Power): ON = connection to external power FD (Fiber Duplex): ON=Full-duplex; Off=Half duplex LNK/ACT (Fiber Link/Activity): ON=Link; Blinking=Activity CD (Copper Duplex): ON = Full-duplex; Off = Half-duplex LNK/ACT (Copper Link/Activity): ON = Link; Blinking = Activity 100 (Copper): Off = 10 Mbps; ON = 100 Mbps
Dimensions	Width: 3.25" [82.55 mm] Depth: 4.8" [121.92 mm] Height: 1" [25 mm]
Power Consumption	External AC/DC; 12 VDC, 0.8A min
Environment	Operating: 0°C to 50°C Humidity: 5% to 90% (non-condensing) Altitude: 0 – 10,000 ft.
Weight	2 lbs. [0.90 kg]
Compliance	Safety: Wall Mount Power Supply: UL Listed; FCC Class A, VCCI Class 1, CISPR22/EN55022 Class A, EN55024, EN61000, CE Mark
Warranty	Lifetime

Power Supply Included

To order the corresponding country specific power supply, add the extension from the list below to the end of the SKU; Ex: SBFTF1011-105-NA

-NA = Country Code

- NA = North America
- LA = Latin America
- EU = Europe
- UK = United Kingdom
- SA = South Africa
- JP = Japan
- OZ = Australia
- BR = Brazil



Ordering Information

SBFTF1011-105

10/100Base-TX (RJ-45) [100 m/328 ft.]
to 100Base-FX 1300nm multimode (ST)
[2 km/1.2 mi.] Link Budget: 11.0 dB

SBFTF1013-105

10/100Base-TX (RJ-45) [100 m/328 ft.]
to 100Base-FX 1300nm multimode (SC)
[2 km/1.2 mi.] Link Budget: 11.0 dB

SBFTF1039-105

10/100Base-TX (RJ-45) 100 m/328 ft.]
to 100Base-FX 1300nm multimode (LC)
[2 km/1.2 mi.] Link Budget: 11.0 dB

SBFTF1014-105

10/100Base-TX (RJ-45) [100 m/328 ft.]
to 100Base-FX 1310nm single mode (SC)
[20 km/12.4 mi.] Link Budget: 16.0 dB

SBFTF1019-105

10/100Base-TX (RJ-45) [100 m/328 ft.]
to 100Base-FX 1310nm single mode (LC)
[20 km/12.4 mi.] Link Budget: 17.3 dB

SBFTF1040-105

10/100Base-TX (RJ-45) [100 m/328 ft.]
to 100Base-X SFP Slot (empty)

Single Fiber Products

SBFTF1029-105

10/100Base-TX (RJ-45) [100 m/328 ft.]
to 100Base-FX 1310nm TX/1550nm RX single
fiber single mode (SC) [20 km/12.4 mi.]
Link Budget: 19.0 dB

SBFTF1029-106

10/100Base-TX (RJ-45) [100 m/328 ft.]to
100Base-FX 1550nm TX/1310nm RX single
fiber single mode (SC) [20 km/12.4 mi.]
Link Budget: 19.0 dB

Optional Accessories (sold separately)

SFP Modules

Wide Input (24 - 60 VDC) Power Supplies

SPS-2460-PS

Piggy Back Power Supply

SPS-2460-SA

Stand-Alone Power Supply

Mounting Options

E-MCR-05

12-slot Media Converter Rack

RMS19-SA4-01

4-slot Media Converter Shelf

WMBD

DIN Rail Bracket 5" [127 mm]

WMBD-F

DIN Rail Bracket (flat) 3.3" [84 mm]

WMBL

Wall Mount Bracket 4" [102 mm]

WMBV

Vertical Wall Mount Bracket 5" [127 mm]