



PS210

- BUILT TO RUN UP TO 2 LOCKS, EXIT TRIM & LP MOTOR/SOLENOID DEVICES
- ROBUST SOLID-STATE OUTPUTS - PROTECTS SYSTEM RELAYS
- ROCK SOLID BOARD DESIGN IMPROVES RELIABILITY
- BUILT TO LAST IN THE USA

PS210 - 110-120VAC input power supplies that deliver (1.5) amps @ 24VDC to (1) PTC fused outputs. (1) solid-state input triggers, protects system relays from shorts, grounds and surges. It's regulated linear design makes it a perfect match for electric locks, motor or solenoid driven exit devices, electric strikes, and mag locks.

SPECIFICATIONS

INPUT VOLTAGE:

- 120 VAC, 60 Hz,
- Input Fuse: 2 Amp Fuse @ 250VAC

OUTPUT VOLTAGE:

- 2A @ 24VDC
- 1 Solid State I/O's - 2A auto resetting fused outputs
- Over-voltage protection
- Output Voltage trim pot

FIRE ALARM:

- Fire alarm tie-in

ELECTRICAL:

- Temperature range: 0 to 49° C; 32 to 120° F
- Maximum humidity: 85%

LED's:

- Red = A/C Power indicator
- Green = D/C Output indicator

FEATURES & BENEFITS:

- Linear design insures ample inrush/hold current for latch retraction
- Door mounted LED Power Indicator
- Easy to remove euro connectors

LISTINGS:

- UL294 6th Edition

MECHANICAL DETAILS:

- Enclosure dimensions: PS210 (11" W x 11" H x 4" D).
- 1/2" & 3/4" knockouts on all sides
- Hinge-less removable cover; Cam lock not provided
- Product Weight: PS210 - 10lbs
- Shipment Weight: PS210 - 11lbs

Part #

PS210

Easy Order #

78850

Description

w/o battery back up.

U.S. Customer Support
1-888-622-2377
Visit our website for more details
www.CommandAccess.com
Canada Customer Support
1-855-823-3002

Command Access is not a licensee, or affiliated, associated or connected with Allegion, Assa Abloy, Stanley, Schlage, Falcon, Von Duprin, Dorma, Sargent, Corbin Russwin, Yale, Emtek, Adams Rite, Best, Precision, Arrow, Design Hardware, Cal Royal, Jackson, AHT, Marshall Best, Marks, Accurate, Baldwin, FSB, PDQ, Lawrence, Trans Atlantic, Hager, LSDA, General Lock, or Omnia or any of their subsidiaries or affiliates.

Doc #20230_D

POWER SUPPLY MATRIX

	24VDC PS Line	Amperage(Continuous)	Boost Current ⁵	Inputs	Outputs (fused)	Battery Back-up (Batteries Not Included)	Fire Alarm Link	24V Power Tap (Constant power)	Locking Hardware (Mortise/Cylindrical/Exit Trim)	Latch Retraction (with LPM, PM300HO)	Latch Retraction (with PM300/Solenoid)	Latch Retraction (with MM Module/Motor)	Metal Enclosure
UL294 6E	PS204	2	3	4	4	-	✓	-	4	-	-	4	S
	PS204B	2	3	4	4	✓	✓	-	4	-	-	4	L
	PS210	1.5	2.5	1	1	-	- ¹	-	2 ²	2 ²	2 ²	2 ²	S
	PS220	2	3	2	2	-	✓	✓	2	2	2	4	S
	PS220B	2	3	2	2	✓	✓	✓	2	2	2	4	L
	PS440B	4	6	4	4	✓	✓	-	4	3	4	4	L
	PS480B	4	6	8	8	✓	✓	-	8	0	8	8	L
UL294	PS1	1	-	1	1	-	- ¹	-	2 ²	2 ²	2 ²	2 ²	S
	PS2 ⁴	2	-	2	2	-	✓	-	2	0	2	2	L
	PS2BB ⁴	2	-	2	2	✓	✓	-	2	0	2	2	L
	PS5	5	-	0	1	✓	✓	-	8 ³	6 ³	8 ³	8 ³	L
	PS5-4	5	-	4	4	✓	✓	-	4	4	4	4	L
	PS5-8	5	-	8	8	✓	✓	-	8	0	8	8	L

Small Enclosure: 11" x 11" x 4"

Large Enclosure: 13" x 15.5" x 5"

1. Uses Fire Alarm tie-in through trigger.

2. 1 output powers 2 devices/locks simultaneously

3. Up to stated devices/locks depending on distribution board or relays (by others).

4. Add Suffix (BO) for board only. Will not include metal enclosure.

5. Boost Current: Max current allowed by UL at 20% duty cycle.