

### Miniature 315MHz 1-Channel RF Receivers & Transmitters

**SK-910RAQ** 1-Channel Receiver – 3Amp Relay Output

**SK-910RAVQ** 1-Channel Receiver – Transistor Group O/P

- Four programmable output modes:
  - 4-Second Momentary Output
  - Validity Output
  - Toggle Output
  - 1-Second Momentary Output
- Flexible operating voltage: SK-910RAQ: 11~24 VAC/VDC  
SK-910RAVQ: 3-13.8 VDC
- Up to 500ft (152m) range\*, 315MHz
- Controls garage doors, gates, house lights, alarm panels, or other devices via remote
- Compatible with all 315MHz SECO-LARM transmitters (fixed code and CODEBUMP™)
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode



SK-910RAQ

**SK-919TD1S-UPQ** Factory Pre-Coded Transmitter

**SK-919TT1S-BU** DIP-Switch-Coded Transmitter

- Operates up to 500ft (152m)\*, 315MHz
- LED transmission indicator
- Includes 12VDC alkaline battery
- Compatible with all 315MHz SECO-LARM receivers
- SK-919TD1S-UPQ: Over 68 billion possible codes
- SK-919TT1S-BU: Use for "block coding" a large number of transmitters with the same code, or for simple matching of a transmitter already in use



SK-919TD1S-UPQ



SK-919TP1H-BUQ

**SK-919TP1H-BUQ** 1-Button Handheld Transmitter

- Operates up to 500ft (152m)\*, 315MHz
- Over 68 billion (6.8x10<sup>10</sup>) possible codes
- Includes two 3VDC lithium batteries
- Visor clip and belt clip included. Belt-clip holster & wall-mount bracket also available (Model: SK-9HBC)
- Slimline design
- Low battery indicator – LED flashes when battery drops below 2VDC
- Compatible with all 315MHz SECO-LARM receivers

### SK-910RAQ and SK-910RAVQ Specifications:

| Model             | SK-910RAQ  | SK-910RAVQ                             |
|-------------------|--|--|
| Range             | Up to 500' (150m) in open air  |  |
| Operating voltage | 11~24 VAC/VDC  | 3~13.8 VDC                             |
| Current Draw      | 5mA Standby, 50mA LED flashing @ 12VDC   | 5mA Standby, 15mA LED flashing @ 12VDC |
| Output Mode       | Programmable 4-sec momentary (default), 1-sec momentary, toggle (ON/OFF), validity |  |
| # of outputs      | 1  | 1                                      |
| Output Type       | 3A Relay (NO/NC/COM)   | 5A Transistor GND                      |
| Transmitter       | Compatible with all 315MHz SECO-LARM transmitters                                  |  |

\*Actual range may vary greatly depending on the installation and operating environment.

### SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: [www.seco-larm.com](http://www.seco-larm.com) Email: [sales@seco-larm.com](mailto:sales@seco-larm.com)



Copyright © 2017 SECO-LARM U.S.A., Inc. All rights reserved. All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners. The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA SLI®

PI\_SK-910RAVQ\_170215.docx