

AL600ULXD Power Supply/Charger

Rev. DSAL600ULXD - J16G



Overview

• The AL600ULXD power supply converts a 115VAC or 230VAC / 50/60Hz input, to a 12VDC or 24VDC non-power limited output.

Specifications

- Switch selectable 12VDC or 24VDC non-power limited output.
- 12VDC or 24VDC @ 6 amp supply current.
- Input 115VAC / 60Hz, 1.9 amp or 230VAC 50/60Hz, .95 amp.
- Maximum charge current .7 amp.
- Filtered and electronically regulated output.
- Built-in charger for sealed lead acid or gel type batteries.
- Automatic switch over to stand-by battery when AC fails.

- AC input and DC output LED indicators.
- AC fail supervision (form "C" contacts).
- Low battery and battery presence supervision (form "C" contacts).
- Short circuit and thermal overload protection.
- Unit is complete with power supply, enclosure, cam lock and open frame transformers.
- Includes battery leads.

Agency Approvals



UL 294

UL Listed for Access Control System Units.

UL 1481 UL Listed Standard for Safety for Fire Protective Signaling Systems.



European Conformity.

Enclosure Dimensions

15.5"H x 12"W x 4.5"D

