



SLP-UL-M-KIT

- PTS "PUSH TO SET" TECHNOLOGY - EASILY POST- INSTALLATION ADJUSTMENTS
- ELECTRONIC DOGGING - NO NEED FOR MECHANICAL DOGGING
- QUICK & EASY INSTALLATION
- WORKS ON ALL SARGENT 80 SERIES 36" & 48" DEVICES



The **SLP-UL-M-Kit** is a field retrofit accessory package to convert a mechanical Sargent 80 series device to an electrified latch pullback device and maintain the UL Listing. This easy-to-install, motor-driven kit from Command Access comes with our "Push to Set" technology that making post installation adjustments incredibly easy.



Scan or
Click Me

SPECIFICATIONS

VOLTAGE:

- Voltage range – 22 to 28 VDC
- System protection – unit shutdown when voltage exceeds 28VDC
- Average In-rush Current – 1A
- Average Hold Current -180mA
- PTS adjustment – approx. 1/4"

WIRE RUN:

- 500' with 18ga wire
- 700' with 16ga wire

PRODUCT DETAILS:

- Box: 10.5" x 3.75": x 2.5"
- Weight: 2 Lbs
- 15 Master Pack Qty: 30 Lbs
- Master Pack Box: 12.75 x 11.75": x 11"

RECOMMENDED UL LOCKING HARDWARE POWER SUPPLIES:

- | | |
|----------------|----------|
| • PS204/PS204B | • PS480B |
| • PS210 | • PS1 |
| • PS220/220B | • PS2 |
| • PS440B | • PS5-8 |

FEATURES:

- MM3 Smart Module: On board diagnostics with audible feedback for adjustment and power issues
- "PTS": 5 second electronic adjustment for easy post installation adjustment
- Electric dogging rated for continuous duty - Auto retraction if dogged push pad is pulled from position
- Low current draw
- Up to 500' wire run with 2-18ga wire - Long wire runs provides installer with convenience of placing the locking device power supply in a centralized location; i.e. the same closet as the access panel
- 6' cable with Quick Connect for MM3 module to easily connect to power supply lead
- 3-year "no hassle" warranty

ACCESSORIES:

- Request to Exit (REX) - Available as a field installable kit or factory installed

HOW TO ORDER

Part #	Easy Order #	Description
SLP-UL-M-KIT	70141	Kit for the Sargent 80. EU 24 VDC.

U.S. Customer Support
1-888-622-2377

Visit our website for more details
www.CommandAccess.com

Canada Customer Support
1-855-823-3002

Command Access is not a licensee, or affiliated, associated or connected with Allegion, Assa Abloy, Stanley, Schlage, Falcon, Von Duprin, Dorma, Sargent, Corbin Russwin, Yale, Emtek, Adams Rite, Best, Precision, Arrow, Design Hardware, Cal Royal, Jackson, AHT, Marshall Best, Marks, Accurate, Baldwin, FSB, PDQ, Lawrence, Trans Atlantic, Hager, LSDA, General Lock, or Omnia or any of their subsidiaries or affiliates.

Doc #20219_B