

# FLP-UL-M-KIT

- PTS "PUSH TO SET" TECHNOLOGY
- EASY TO INSTALL - "DROP-IN" KIT.
- FULL PUSH PAD RETRACTION -- FOR TRUE ELECTRONIC DOGGING
- WORKS ON 24/25 SERIES
- UL LISTED
- 3 YEAR "NO HASSLE" WARRANTY



The **FLP-UL-M-Kit** is a practical and cost-effective way to convert a mechanical Falcon 24 and 25 series device to an electrified latch pullback device. Our easy-to-install motor -driven kit installs in a matter of seconds with no drilling or screws required, a true "drop-in" kit! The retrofit kit will maintain all UL listings on the device and is backed by CAT's 3-year no hassle warranty. **Push To Set** allows for an easy post-installation adjustment of the latch/latches. A built-in REX switch is standard on all units! Last but not least, all new FLP-UL-M-KIT's features an updated **MM4S** module with 3 different energy consumption settings from energy conscious to high torque to get the tough jobs done!

## SPECIFICATIONS

### VOLTAGE:

- Voltage range – 24 to 28 VDC
- System protection – unit shutdown when voltage exceeds 28VDC
- **Standard** - Average Current Peak: 900MA, Average Current Hold: 215mA
- **Low Current** - Average Current Peak: 600MA, Average Current Hold: 150mA
- **High Torque** - Average Current Peak: 2A, Average Current Hold: 250mA
- PTS adjustment – approx. 1/4"

### WIRE RUN:

- 300' with 18ga wire

### PRODUCT DETAILS:

- Box: 10.5" x 3.75": x 2.5"
- Weight: 2 Lbs
- 15 Master Pack:
- Weight: 30 ILbs 12.75" x 11.75" x 11"

### CUTDOWN DETAILS:

- 36" Model - Max Cut 2"

### FEATURES:

- Next Generation MM4S Smart Module: On board diagnostics with audible feedback for adjustment and power issues
- "PTS": 5 second electronic adjustment for easy post installation adjustment
- Electric dogging rated for continuous duty - Auto re-engage if push pad is pulled from dogged position
- Low Current Draw - Field switchable to a "Low Current" or "High Torque" mode
- Up to 300' wire run with 2-18ga wire - Long wire runs provides installer with convenience of placing the Command locking hardware power supply in a centralized location; i.e. the same closet as the access control panel
- 8' cable with Quick Connect for MM4S module to easily connect to power supply lead
- Request to Exit (REX) built-in at no charge
- 3-year "no hassle" warranty

**U.S. Customer Support**

**1-888-622-2377**

**Visit our website for more details**

**www.CommandAccess.com**

**Canada Customer Support**

**1-855-823-3002**

Command Access is not a licensee, or affiliated, associated or connected with Allegion, Assa Abloy, Stanley, Schlage, Falcon, Von Duprin, Dorma, Sargent, Corbin Russwin, Yale, Emtek, Adams Rite, Best, Precision, Arrow, Design Hardware, Cal Royal, Jackson, AHT, Marshall Best, Marks, Accurate, Baldwin, FSB, PDQ, Lawrence, Trans Atlantic, Hager, LSDA, General Lock, or Omnia or any of their subsidiaries or affiliates.

*Doc #20360\_A*

## How to Order

Part #	Easy Order #	Description
<b>FLP-UL-M-KIT</b>	<b>79338</b>	Kit for the Falcon 24/25 series. EU 24 VDC w/ REX.

## FLP-UL-M-KIT MATRIX

The FLP-UL-M-KIT will work in new installations and as a replacement for installations with existing electrifications, matrix lists available options.

Falcon Kit		Mechanical unmodified	CAT Modified Motor	Falcon Solenoid (EL)	SDC Motor (LR100-FRK)	ACSI Motor (1550-MDF)
<b>FLP-UL-M-KIT</b>	24/25	✓	✓	✓	✓	✓

### NEED A LOCKING HARDWARE POWER SUPPLY?

#### RECOMMENDED LOCKING HARDWARE POWER SUPPLIES:

- PS204/PS204B
- PS210
- PS220/220B
- PS440B
- PS480B
- PS1
- PS2
- PS-4
- PS5-8

